



PROGRAMMING THE GLOBECAST RECEIVER FOR Home2US FREE SERVICE

On the remote control press MENU (The Main Menu will appear on the screen)
Press the up or down arrow on the remote to go to [Setup]
Press the right arrow to go to the Setup List on the right
Go to (7) [Factory Default] with the down arrow
Press OK on the remote
Enter Password 0000 (4x zero)
With the UP arrow highlight [OK]
Press OK on the remote

After the reset a Message Box will appear with “No Program found”
Press OK on the remote
After the Main Menu appears go down to [Setup]
With the right arrow go to the list on the right
Go to (2) [Antenna Setup]
Press OK on the remote
Go down to [GlobeCast]
Press the right arrow until [Newsat01] appears
Press EXIT on the remote
Press the right arrow on the remote. (Ok appears)
Press OK on the remote. (The Main Menu appears)
Go down to (3) [Channel Search]
Press OK on the remote
Go down to [TP1]
Press the red button on the remote (2x [New] appears)
Go down to the first [New]
With numerical keys input 12120
Go down to the second [New]
With the numerical keys input 30000
Go up to [Newsat01]
Press the yellow button on the remote. (The keypad appears)
Go down to “A” and press OK on the remote
Go to “M” and press OK on the remote
Go to “C” and press OK on the remote
Go to “4” and press OK on the remote
Go all the way down to [Ok] so it is highlighted
Press OK on the remote
Go all the way down to [Search Network]
Press the right arrow on the remote until [Search TP] appears
Press OK on the remote. (A search is started)
Go to [Exit] so it is highlighted
Press OK on the remote
Press EXIT on the remote
By pressing OK on the remote a list of available channels will appear.
Choose the desired channel and press OK on the remote
By pressing EXIT on the remote, the channel list will disappear